

LogiLink

VGA with Audio to HDMI Converter

Art. No.: CV0060

This VGA with Audio to HDMI converter allows you to connect analog VGA video signal to a digital HDMI display; comes with 3.5mm audio input for combining audio into the HDMI output.



- » Compliant with High Speed HDMI
- » Compatible with PC VGA resolutions 480i/480p/576i/576p/720p/1080i/1080p
- » HDMI transmission rate: 4.95 Gbps
- » Supports 165 MHz/1.65 Gbps per channel (4.95 Gbps all channels) bandwidth
- » Supports 12 bit per channel (36 bit all channels) deep color
- » Supports uncompressed 2 channel audio such as LPCM
- » Cable length: 15 cm
- » Product dimensions: 5.4x3.7x1.3 cm
- » Product weight: 0.05 kg





*The specifications and pictures are subject to change without prior notice. *All trade names referenced are the registered trademarks of their respective owners.



3.7 cm

LogiLin

5.4 cm



LogiLink

VGA with Audio to HDMI Converter

Art. No.: CV0060

Specifications:

Input	VGA, male
Input Video Signal	0.5–1.0 volts p-p
Output	HDMI-A, female
Resolution	480i/576i/480p/576p/720p/1080i/1080p
Video Amplifier Bandwidth	1.65 Gbps/165 MHz
Vertical Frequency Range	50/60 Hz
Operating Temperature	0–70 °C
Operating Humidity	10–85% RH (no condensation)
Storage Temperature	-10–80 °C
Storage Humidity	5–90% RH (no condensation)
Power Connection	USB Power cable
Power Consumption	5 W max.

Package Contents:

- » 1 x VGA with audio to HDMI Converter
- » 1 x Audio Cable
- » 1 x USB Cable
- » 1 x User Manual

Package Information:

- » Packing Dimension: 137x146x16mm
- » Packing Weight: 0.075 kg
- » Carton Dimension: 575x235x340 mm
- » Carton Q'ty: 160 pcs
- » Carton Weight: 12.7 kg









*The specifications and pictures are subject to change without prior notice. *All trade names referenced are the registered trademarks of their respective owners.

Made in China